

تخصیص	
اسم المنتج	دس داخلي بير + الميكروويف كاشف الحركة المضادة للحيوانات الاليفة 12V
نموذج	EB-172
بحجم	(ملم) 128 * 65 * 41
طاقة كهربائية شغالة	9 ~ 13.5V دس
تيار ثابت	(العاصمة امدادات الطاقة vتحت 25uA (12)
إنذار الحالي	(العاصمة امدادات الطاقة ٧تحت 15mA (12
مو	حساسية 30٪ ~ 100٪ قابل للتعديل ،12 * 12m
تغطية بير	12 * 12M
كشف زاوية	درجة 110
درجة حرارة العمل	-10 °C ~ 50 °C
درجة حرارة التخزين	-25 °C ~ 65 °C
EMI مكافحة	<sub>9</sub> GT، 300V / M
مكافحة الضوء التدخل	<sub>9</sub> GT، 6500LUX
اللون	أبيض
وزن	0.1KG

# كاشف الميكروويف؟ + PIRما هي ميزات لدينا 172



- 1.Wired MW+PIR intelligent motion detector
- 2.9~13V DC power supply
- 3.3 LED indicator light
- 4. Compatible all kinds of alarm system's wired zones
- 5.2 years warranty, welcome OEM

# إن-كيند شوتينغ

















## كيفية استخدامها



3.5. Working status Setup



T

LED Jumper: LED is on when it's connected and out when it's

disconnected

PIR optional Jumper: PIR is available when connected (normal on) and unavailable when disconnected with only single iron Transcuder is available

M\_EN Microwave choose jumper: Microwave function effectively when connected, disconnected become single infrared microwave function is cancelled




PIR distance jump line: When connected 4 to 8 meters, detection range of 4 to 8 meters. When connected 6 to 12 meters, detection range of 6 to 12 meters, When connected 9 to 18 meters, detection range of 9 to 18 meters.

MPULSE counting jump line: The factory set up to 20. When the pulse number is 30 alarm response is slow, and detection range, strong anti-jamming capability, when the pulse number is 10 alarm response speed, anti-interference to weak, choosing to 30, should disconnect the LED jump line

MADI sensitivity adjustable: When the yellow light is on for 30s or microwave detector tor hypertelorism MIN direction adjustment. When microwave detector adjusted distance is too close to the MAX.

PIR PLUSE JUMPER LINE: Connected position pulse counting 1 to 1, connected pulse counting at position 2 to 2 (factory Settings pulse counting to 2)






# **Apperance**


# MW+PIR+Intelligent Motion Detector EB-172






**PCB** board

# **Detecting distance**



Common wiring way



Wiring way













This model wired motion detector product is widely use in all kinds of burglar alarm system, Such as Villa ,Home ,Factory, Warehouse, Office, Bank etc.

## الأصناف المتعلقة



التعبئة & أمبير؛ الشحن



# عرض المكتب













#### **CUSTOMER**













## معرض



# شهادة



#### التعليمات

#### س: يمكنني الحصول على عينة النظام؟

ا:نعم، نحن مستعدون لتقديم محاكمة النظام عينة لَّكُ لاختبار الجودة. عينات مختلطة مقبولة

#### س: ما هي المهلة؟

. ا: عينة يحتاج 1-3 أيام عمل، وقت الإنتاج الضخم يحتاج 10-15 أيام عمل لأجل أقل من 5000 قطع

# س: هل لديك أي موك الحد؟

ا:إكسو موك هو 100 قطع تحت مربع فارغ

#### س: كيف تقوم بشحن البضاعة وكم يستغرق يستغرق تصل؟

ا:وسوف ترسل عينة لك من قبل خدمة الشحن اختياري (السعاة، الهواء، والبحر). وقت التسليم يعتمد على خدمة الشحن السعن الس

#### س: كيف يمكننا المضى قدما النظام إذا كان لدي شعار لطباعة؟

ا:أولا، سوف نستعد الفني للتأكيد البصري. إذا كان اللون والموقف على حق، ونحن جُعل أخذ العينات أولاً من الحرير طباعة المصنع و التقاط صورة لتأكيد الثاني قبل الإنتاج بكثافة الإنتاج بكميات ضخمة.