□□□□ RS485 □□□□□□□□□ □□□□ □□ □□□□□□ □□□□ □□□□ □□□

EB-82's MAIN PARAMETER

	□□□□□
□□□	□□□□ RS485 □□□□□□□□□ □□□□ □□ □□□□□□ □□□□ □□□□ □□□
□□□□□	EA-82
□□□□□ □□□□□□□□□ □□□□	DC12V ± DC3V
□□□□□ □□□	□□□□□□□ & lt2 □W
□□□□□□□ □□□	EM 4100 □□□□ □□□□ 125 □□□□□
□□□□□□□□ □□□□□□□	□□□ 90 □□□□
□□□□□□□ □□□□	10000
□□□□□□□□□□ □□□□	10000
□□□□□ □□	IP66
□□□□□□□ □□□□□	RS485
□□□□□□□ □□□□	9600bps (N□ 8□1)
□□□□□□□□ □□□□	4M □□□□□ □□ FLASH
□□□□□□□	96L × 96W × 22H (□□)
□□□□□	□□□□□□□□) □□□□ / □□□□)
□□□□	ABS + PCB □□□□
□□□□□□ □□□□□ □□□□	-30 □□□□□ □□□□ 60+ □□□ □□□□□ □□□□
□□□□□ □□□	□□□□□
□□□	260G

1. □□□□□□□ □□ □□□□□ □ □□□□□□ □□□□□□□ □□□□□ □□□□□ □□□ □□ □ □□□ □□□□□ □□ □□□□.

2. □□□□□□□□□ □□□□□□ □□□□□□□ PC □ □□□□□□ □ □□□□□□□ □□□□□□ □ □□□□□□□ □□□□□□ □□□□□□.

3. □□□□□ □□□□□ □□□□ □□ □□□ .□□□□□□□□ □□□□□□□□ □□□□□□□ □□□□□ □□□□□ □□□□□□ □□□□□ 10 □□□□ □□□□□□ □□□ □□□□□ □□□□ □ □□□□□□.

4. □□□□ □□□ .□□□□□ □□□□□□ □□□□□□□□ □□□□ □□□□□ □□□ □ □□□□□□ □□□□□ □□□□□□□□ □□□□ □□ □□□□□ □□□□□□□ □□□□□.

5. .□□□□□ □□□□ □□□□ □□□ □□□□□□□ □ □□□□□□□ □□□□□□□ □□□□□□□ □□ □□□□□□ 100 □□ □□□□□ □□□□□ □□□□□□□ □□□□□ □□□□□□□ □□□□□□ □□□ □□□□□.

6. □□□ □□□□□□ □□□□□ □□□□ □□ □□□□□□□□ □□□□□□ □□□□□ kaypad (□□□□□□□□□□ □□□□□□□□ □□□□ □□ □□□□□ □ (□□□□□□ □□□□□□□□□.

7. □ □□□□□ □□□□ □□□□□□ □□□□□□□ □□□□□□ □□□□□ □□□□□ □□□□□□□ □□□□□□ □□□□□ □□ □□□□□□□ □□□□ □□□ □□□□□ □□□ □□□□□□□ □□□ □□□□□□ □□□ □□□.

8. □□□□□□ □□□□□ □□□□□ □□ .□□□□□ □□□□□□□□□□ □□□□□□ □□□□□ □□ □□□□□□ □□□□□□ □□□□ □□□ □□□□□□ □□□□□□□ □□□□□□ □□□□□ □□□□□ □□□□ □ □□□□□□ □□□□ □□□ □□□□□□□ □□□□□□□□.

9. □□□□□ □□□□□ □□ □ □□□□□□ □□□□□□□ □□□□.

10. □□□□□□□ □□□ □ □□□□□□ □□□□□□ □□□□□ □□ □ □□□□□ □□□□ □□□□□□.

11. □□□□ □□□□□□ □□□□□□ □ □□□□□□□ □□ □□□□□□□ □ □□□□□□ □□□□□□□ □□□□□□□ □□ □□□□□ □□ □□□□□□ □ □□□□□□□.

Appearance

Wiring diagram



Wire port specification		
NO	Function	Description
1	RS485+	Data +
2	RS485-	Data -
3	12V＋	DC Power 12V
4	GND	GND
5	OUT-NC	Door relay NC interface
6	OUT-COM.	Door relay COM interface
7	OUT-NO.	Door relay NO interface
8*	IN 1	Input 1, door release button input
9*	IN 2	Input 2, door magnet signal input
10*	IN 3	Input 3, user-defined
11	OC OUT	Build-in doorbell signal output
12*	OUT 2	OC signal, duress output
13*	OUT 3	OC signal, anti-tamper output
14	GND	GND
15	OUT 12V+	Power output, can be connected to WG reader power +
16	GND	Power output, can be connected to WG reader power GND
17	DATA 0	WG Data 0 input, connect reader Data 0
18	DATA 1	WG Data 1 input, connect reader Data 1
19	GND	GND
20	OC1-OUT	Unregistered card output, OC signal output for 3s after card flashing to open the door, can connect Green LED end of WG reader.
21	OC2-OUT	Unregistered card output, OC signal output for 3s after card flashing but not to open the door, can connect Red LED end of WG reader.
22	OC3-OUT	Unregistered card output, OC signal output for 3 times after card flashing to open the door, each interval time is 100ms, can connect Beeper end of WG reader.
23	NULL	N/A
24	ANTI-TAMPER-IN	Anti-tamper signal input, connect anti-tamper output signal of WG reader

Installation



:mm



□□□□ □□□□ □□□ □□□

SMQT
铭汗科技
SMQT
铭汗科技
SMQT
铭汗科技
CARD HERE
CARD HERE
SMQT
铭汗科技
请刷卡
Please read card
SMQT
铭汗科技
ACCESS
ACCESS
SMQT
铭汗科技
ACCESS CONTROL
SMQT
铭汗科技
SMQT
铭汗科技
SMQT
铭汗科技