

**SMQT plastic shell hindi tinatablan ng tubig IP66 6 wire WG format pinto
access control mambabasa**



ANO ANG EA-62 TINGNAN?



EA-62'S MAIN PARAMETER

Produkto Pangalan:	SMQT plastic shell waterproof IP66 6 wires WG format ng pag-access ng access control reader
Numero ng modelo:	EA-62
Kapangyarihan supply:	DC 12V
Kasalukuyang Paggawa:	& lt; 100mA
Uri ng Kard:	IC card (13.56MHz)
Format ng komunikasyon:	WG26 / WG34 (adjustable)
Reading distance:	5 ~ 15cm
Komunikasyon layo:	& gt; 80m (sa pagitan ng card reader at controller)
Hindi nababasa:	IP66 (angkop para sa panlabas gamitin)
Dimensyon:	117 * 76 * 18 (mm)
Mga Wires:	6 wires

Output ng contact:	12V + (Red wire) / GND (Black wire) / D0 (Green) / D1 (White) / LED (Grey) / WG (Lila)
Angkop para sa:	Control ng access sa pinto ng IC Card sistema
Material:	ABS pabahay + Plexiglass panel + PCB board
Kulay ng pabahay	Itim at Pilak
Timbang:	0.2kg
Garantiya:	2 taon na warranty
OEM:	Maligayang pagdating OEM

ANO MGA TAMPOK NA EA-62 MAYROON?



1. Plastic waterproof door access control IC(13.56MHz) card reader

2. Working voltage DC 8~15V

3. Working current <100mA

4. Card type IC(13.56MHz) Mifare card

5. WG26/WG34 adjustable

6. Reading distance 5~15cm

7. Transmitting distance >80m(from reader to controller)

8. Waterproof **IP66**(suitable for outdoor use)

9. Wire port: DC+ /GND/D0/D1/LED/WG, 6 wires


10. Suitable for all kinds of IC door access control system

11. 2 years warranty , welcome OEM

PAANO TUNGKOL SA PACKAGING NG STANDARD EA-62?



SAAN ANG EA-62 NATING PAMAMAGITAN NG PAG-INSTALL?



Waterproof




High temperature resistance

Wiring diagram



Card reader EA-62


- 12V
- GND
- WG
- LED
- D0
- D1



Access control keypad



Access control power supply



Door release button



Lock

How to adjust WG26/WG34 output?

WG34



Connect the purple and black wires of the card reader to the controller's GND connector.

WG26



Do not connect the card reader's purple wire.

Application site



Apartment



Villa




Home



School



Hospital



Document Room

PAANO TUNGKOL SA IBANG PILIPINAS?

SMQT
铭汗科技



SMQT
铭汗科技



SMQT
铭汗科技



SMQT
铭汗科技



SMQT
铭汗科技



SMQT
铭汗科技



SMQT
铭汗科技



SMQT
铭汗科技



SMQT
铭汗科技

