

## 13.56Mhz Mifare S50 / S70 card supported door access control card reader



### MQ-711's main parameter

<b>Product Name:</b>	13.56Mhz Mifare S50 / S70 card supported door access control card reader
<b>Model number:</b>	<b>MQ-711</b>
<b>Card type:</b>	IC card(13.56MHz)
<b>Power supply:</b>	DC12V
<b>Working current:</b>	<100mA
<b>WG output format:</b>	Default WG34, support WG26, WG34, WG66, the format of WG output can be customized
<b>Reading distance:</b>	0~3CM
<b>Communication distance:</b>	<80m(between card reader and controller)
<b>Waterproof:</b>	<b>IP67</b>
<b>Dimension:</b>	153*45*16.3(mm)
<b>Wires ports:</b>	<b>6 wires</b>
<b>Contact output:</b>	<b>12V+(Red wire)/GND(Black wire)/D0(Green)/D1(White)/Beeper(Purple)/LED(Grey)</b>
<b>Suitable for:</b>	<b>Door access control system</b>

Material:	ABS housing+ PCB board
Housing color	Silver frame+ Black panel
Weight:	0.2kg
Warranty:	1 years warranty
OEM:	Welcome OEM

What features MQ-711 have?

Size



# Appearance



## Wire port introduction



# What type card it can read?



How about other choice?

