

## Plástico SMQT shell impermeável IP66 6 fios WG formato porta controle de acesso leitor



O QUE É QUE EA-62 OLHA COMO?



## EA-62'S PRINCIPAIS PARÂMETROS

|                                |                                                                                                        |
|--------------------------------|--------------------------------------------------------------------------------------------------------|
| <b>produtos Nome:</b>          | Shell de plástico SMQT impermeável IP66 6 leitor de controle de acesso da porta do formato dos fios WG |
| <b>Número do modelo:</b>       | EA-62                                                                                                  |
| <b>Poder fornecem:</b>         | DC 12V                                                                                                 |
| <b>Corrente de trabalho:</b>   | & lt; 100mA                                                                                            |
| <b>Tipo de carta:</b>          | Cartão IC (13,56 MHz)                                                                                  |
| <b>Formato de comunicação:</b> | WG26 / WG34 (ajustável)                                                                                |
| <b>Distância de leitura:</b>   | 5 ~ 15cm                                                                                               |
| <b>Comunicação distância:</b>  | & gt; 80 m (entre o leitor de cartões e o controlador)                                                 |
| <b>À prova d'água:</b>         | <b>IP66 (adequado para exterior usar)</b>                                                              |
| <b>Dimensão:</b>               | 117 * 76 * 18 (mm)                                                                                     |
| <b>Fios:</b>                   | 6 fios                                                                                                 |

|                          |                                                                                                    |
|--------------------------|----------------------------------------------------------------------------------------------------|
| <b>Saída de contato:</b> | <b>12V + (fio vermelho) / GND (fio preto) / D0 (verde) / D1 (branco) / LED (Cinza) / WG (roxo)</b> |
| <b>Adequado para:</b>    | <b>Controle de acesso à porta do cartão IC sistema</b>                                             |
| <b>Material:</b>         | Carcaça ABS + painel de plexiglass + PCB borda                                                     |
| <b>Cor da carcaça</b>    | Preto e prata                                                                                      |
| <b>Peso:</b>             | 0,2 kg                                                                                             |
| <b>Garantia:</b>         | 2 anos de garantia                                                                                 |
| <b>OEM:</b>              | Bem-vindo OEM                                                                                      |

## O QUE CARACTERÍSTICAS EA-62 TEM?











1. Plastic waterproof door access control IC(13.56MHz) card reader

**2. Working voltage DC 8~15V**

3. Working current <100mA

**4. Card type IC(13.56MHz) Mifare card**

**5. WG26/WG34 adjustable**

**6. Reading distance 5~15cm**

**7. Transmitting distance >80m(from reader to controller)**

8. Waterproof **IP66**(suitable for outdoor use)

**9. Wire port: DC+ /GND/D0/D1/LED/WG, 6 wires**

**10. Suitable for all kinds of IC door access control system**

**11. 2 years warranty , welcome OEM**

**COMO SOBRE A EMBALAGEM PADRÃO DA EA-62?**




**ONDE ESTÁ O EA-62 APROPRIADO PARA A INSTALAÇÃO?**









Waterproof




High temperature resistance

## Wiring diagram



Card reader EA-62


- 12V
- GND
- WG
- LED
- D0
- D1



Access control keypad



Access control power supply



Door release button



Lock

## How to adjust WG26/WG34 output?

### WG34



Connect the purple and black wires of the card reader to the controller's GND connector.

### WG26



Do not connect the card reader's purple wire.

## Application site



Apartment



Villa



Home



School



Hospital



Document Room

## COMO SOBRE OUTRA ESCOLHA?

**SMQT**  
铭汗科技



**SMQT**  
铭汗科技



**SMQT**  
铭汗科技



**SMQT**  
铭汗科技



**SMQT**  
铭汗科技



**SMQT**  
铭汗科技



**SMQT**  
铭汗科技



**SMQT**  
铭汗科技



**SMQT**  
铭汗科技

