

SMQT Newest Smart Tuya App Wifi Smart Strobe Alarm Siren with Remote Controller

Smart device

Security home

Happy life



EB-822's main parameter

Specification	
Product name:	SMQT Newest Smart Tuya App Wifi Smart Strobe Alarm Siren with Remote Controller
Model:	EB-822
App functions:	App remotely arm/disarm Parameter setting and accessory management Rename defense zone
Learning/storage location:	Support up to 24 wireless detectors and 8 remote controller
Network:	Support Wi-Fi&GPRS network alarm system Support different alarm channels (App push/SMS/voice monitoring/ center alarm, to ensure the alarm performance stable and reliable)
Defense zone supports:	Support gate, SOS, bedroom, window, balcony, perimeter, smoke, gas, carbon monoxide, water leaking
Power/Battery/Tamper alert function:	main power failure / backup battery power shortage.

Door bell function:	Door bell sound: "Ding-dong"
Input voltage:	AC220V/5V DC
Alarm current:	<300mA
Standby current:	<40mA
Wireless frequency	433MHz
Wireless coding	EV1527
Wi-Fi standard	IEEE802.11b/g/n wireless standard
Backup battery	3.7V/300mAh Lithium battery
Relative humidity	<80%RH
Working temperature	0 to 50°C

Features

1. Based on the TUYA smart home platform, work with most of the TUYA smart based smart products.
2. On-site high-decibel alarm, flashing lights and other alarm modes.
3. Home Arm, Away Arm, Disarm
4. Low-battery detection
5. System power off detection.
6. Tamper detection.
7. Built-in battery.
8. Support Amazon Alexa, Google Assistant.

What features EB-822 have?

Standard kit



How does it working?



Tuya Smart



iOS

Android

Siren host



Size:65(diameter)×35mm

Wireless frequency:433Mhz

Built-in backup battery:3.7V/300mAh

Power supply:DC5V 2A

PIR detector



Size:110×52×35mm

Wireless frequency:433Mhz

Wireless transmission distance:100~150m

Battery :6F 22 Battery

Battery life time:1~2 years

Door sensor



Size:

Reed part:65×25×13mm

Magnet part:52×11×13mm

Wireless frequency:433Mhz

Wireless transmission distance:100~150m

Battery : Battery

Battery life time:1~2 years

Remote controller



Size:56×32×12mm

Wireless frequency:433Mhz

Wireless transmission distance:100~150m

Battery : Battery

Battery life time:1~2 years

Door bell trigger button



Size:50(diameter)×15mm

Wireless frequency:433Mhz

Wireless transmission distance:100~150m

Battery : Battery

Battery life time:1~2 years

Power supply adapter



Input:AC110~220V

Ouput:DC 12V 2A

Plug stanard:EU/US/GB etc(optional)

How about other choice?

SMQT
铭汗科技



SMQT
铭汗科技



SMQT
铭汗科技



SMQT
铭汗科技



SMQT
铭汗科技



SMQT
铭汗科技

